

Colorimetric data for system lines NRS18 -> ORS18, TLS00, NRS18, SRS18

For input LCH^*_{a0} (NRS18) and output olv^*_{3m} for 4 systems ($m = 0$ to 4)
Six CIELAB hue angles of device ORS18: (37.7 96.4 150.9 236.0 305.0 353.7);
Six CIELAB hue angles of device TLS00: (40.0 102.8 136.0 196.4 306.3 328.2);
Six CIELAB hue angles of device NRS18: (25.5 92.3 162.2 217.0 271.7 328.6);
Six CIELAB hue angles of device SRS18: (30.0 90.0 150.0 210.0 270.0 330.0);

no.	Colour	->NRS18 LCH^*_{a0}	->NRS18 n^*, c^*, H^*_{a0}	ORS18 olv^*_{31}	TLS00 olv^*_{32}	NRS18 olv^*_{33}	SRS18 olv^*_{34}
01	R=r00j	52.8 38.5 25	0.3 0.5 25	0.7 0.2 0.34	0.7 0.2 0.3	0.7 0.2 0.2	0.7 0.2 0.24
02	r10j	52.8 36.2 32	0.3 0.5 32	0.7 0.2 0.26	0.7 0.2 0.26	0.7 0.25 0.2	0.7 0.22 0.2
03	r20j	52.8 34.4 39	0.3 0.5 39	0.7 0.21 0.2	0.7 0.2 0.21	0.7 0.3 0.2	0.7 0.27 0.2
04	r30j	52.8 33.1 46	0.3 0.5 46	0.7 0.27 0.2	0.7 0.25 0.2	0.7 0.35 0.2	0.7 0.33 0.2
05	r40j	52.8 32.5 52	0.3 0.5 52	0.7 0.32 0.2	0.7 0.3 0.2	0.7 0.4 0.2	0.7 0.38 0.2
06	r50j	52.8 32.3 59	0.3 0.5 59	0.7 0.38 0.2	0.7 0.35 0.2	0.7 0.45 0.2	0.7 0.44 0.2
07	r60j	52.8 32.6 66	0.3 0.5 66	0.7 0.44 0.2	0.7 0.41 0.2	0.7 0.5 0.2	0.7 0.5 0.2
08	r70j	52.8 33.2 72	0.3 0.5 72	0.7 0.49 0.2	0.7 0.45 0.2	0.7 0.55 0.2	0.7 0.55 0.2
09	r80j	52.8 34.4 79	0.3 0.5 79	0.7 0.55 0.2	0.7 0.51 0.2	0.7 0.6 0.2	0.7 0.61 0.2
10	r90j	52.8 36.3 86	0.3 0.5 86	0.7 0.61 0.2	0.7 0.57 0.2	0.7 0.65 0.2	0.7 0.67 0.2
11	J=j00g	52.8 38.6 92	0.3 0.5 92	0.7 0.66 0.2	0.7 0.61 0.2	0.7 0.7 0.2	0.68 0.7 0.2

Goal: Transfer coordinates LCH^*_{a0} (system $m=0$) to $rgb^*_{3m} = olv^*_{3m}$ (system $m=1$ to 4)

The given data LCH^*_{a0} include the device hue H^*_{a0}

Integer (i) device hue: $H^*_{a0} = \text{round} (H^*_{a0})$ (1)

Fetch device data $LCH^*_{a,Mm}$ from table with 361 entries for H^*_{a0} from 0 to 360 degrees

Lightness, chroma, hue: $LCH^*_{a,M0} = LCH^*_{a,M0} [H^*_{a0}]$ (2)

Calculate lcw^*_{a0} data from LC^*_{a0} and $LC^*_{a,M0}$:

Relative lightness: $L^* = [L^*_{a0} - L^*_{N0}] / [L^*_{W0} - L^*_{N0}]$ (3)

Relative chroma: $c^* = C^*_{a0} / C^*_{a,M0}$ (4)

Relative Blackness: $n^* = 1 - l^* + c^* [L^*_{M0} - L^*_{N0}] / [L^*_{W0} - L^*_{N0}]$ (5)

Fetch device data $olv^*_{3,Mm}$ from table with 361 entries for H^*_{a0} from 0 to 360 degrees

"red, green, blue" rgb^*_{3Mm} data: $olv^*_{3,Mm} = olv^*_{3,Mm} [H^*_{a0}]$ (6)

For any input or output device ($m=0$ to 4) it is valid for constant n^*, c^*, l^*, H^*_{a0} :

"red, green, blue" rgb^*_{3m} data: $olv^*_{3m} = 1 - n^* - c^* + c^* olv^*_{3,Mm}$ (7)

Result: device dependent relative CIELAB data of 4 systems $m=1$ to 4:

"red, green, blue" rgb^*_{3m} data: $rgb^*_{3m} = olv^*_{3m}$ (8)

Colorimetric data for system lines NRS18 -> ORS18, TLS00, NRS18, SRS18

For input olv^*_{30} (NRS18) and output olv^*_{3m} for 4 systems ($m = 0$ to 4)
Six CIELAB hue angles of device ORS18: (37.7 96.4 150.9 236.0 305.0 353.7);
Six CIELAB hue angles of device TLS00: (40.0 102.8 136.0 196.4 306.3 328.2);
Six CIELAB hue angles of device NRS18: (25.5 92.3 162.2 217.0 271.7 328.6);
Six CIELAB hue angles of device SRS18: (30.0 90.0 150.0 210.0 270.0 330.0);

no.	Colour	->NRS18 $olv^*_{30} = rgb^*_{30n^*, c^*, H^*_{a0}}$	->NRS18 olv^*_{30}	ORS18 olv^*_{31}	TLS00 olv^*_{32}	NRS18 olv^*_{33}	SRS18 olv^*_{34}
01	R=r00j	0.7 0.2 0.2	0.3 0.5 30	0.7 0.2 0.34	0.7 0.2 0.3	0.7 0.2 0.2	0.7 0.2 0.24
02	r10j	0.7 0.25 0.2	0.3 0.5 35	0.7 0.2 0.26	0.7 0.2 0.26	0.7 0.25 0.2	0.7 0.22 0.2
03	r20j	0.7 0.3 0.2	0.3 0.5 41	0.7 0.21 0.2	0.7 0.2 0.21	0.7 0.3 0.2	0.7 0.27 0.2
04	r30j	0.7 0.35 0.2	0.3 0.5 47	0.7 0.27 0.2	0.7 0.25 0.2	0.7 0.35 0.2	0.7 0.33 0.2
05	r40j	0.7 0.4 0.2	0.3 0.5 53	0.7 0.32 0.2	0.7 0.3 0.2	0.7 0.4 0.2	0.7 0.38 0.2
06	r50j	0.7 0.45 0.2	0.3 0.5 60	0.7 0.38 0.2	0.7 0.35 0.2	0.7 0.45 0.2	0.7 0.44 0.2
07	r60j	0.7 0.5 0.2	0.3 0.5 67	0.7 0.44 0.2	0.7 0.41 0.2	0.7 0.5 0.2	0.7 0.5 0.2
08	r70j	0.7 0.55 0.2	0.3 0.5 73	0.7 0.49 0.2	0.7 0.45 0.2	0.7 0.55 0.2	0.7 0.55 0.2
09	r80j	0.7 0.6 0.2	0.3 0.5 79	0.7 0.55 0.2	0.7 0.51 0.2	0.7 0.6 0.2	0.7 0.61 0.2
10	r90j	0.7 0.65 0.2	0.3 0.5 85	0.7 0.61 0.2	0.7 0.57 0.2	0.7 0.65 0.2	0.7 0.67 0.2
11	J=j00g	0.7 0.7 0.2	0.3 0.5 90	0.7 0.66 0.2	0.7 0.61 0.2	0.7 0.7 0.2	0.68 0.7 0.2

Goal: Transfer coordinates olv^*_{30} (system $m=0$) to olv^*_{3m} (system $m=1$ to 4)

The following equations for relative blackness and chroma are valid for any device:

$$n^* = 1 - \max (o^*_{30}, l^*_{30}, v^*_{30}) \quad (1)$$

$$c^* = \max (o^*_{30}, l^*_{30}, v^*_{30}) - \min (o^*_{30}, l^*_{30}, v^*_{30}) \quad (2)$$

For the calculation of the missing relative device hue assume

as a starting point that the three values olv^*_{30} belong to the standard (s) device SRS18:

relative red-green chroma: $a^*_{r0} = o^*_{30} \cos(30) + l^*_{30} \cos(150)$ (3)

relative yellow-blue chroma: $b^*_{r0} = o^*_{30} \sin(30) + l^*_{30} \sin(150) - v^*_{30} \sin(270)$ (4)

Standard integer hue: $H^*_{s0} = \text{round} [\text{atan} (b^*_{r0} / a^*_{r0})]$ (5)

Fetch device integer hue: $H^*_{a0} = H^*_{s0} [H^*_{s0}]$ (6)

Fetch device data $olv^*_{3,Mm}$ from table with 361 entries for H^*_{a0} from 0 to 360 degrees

"red, green, blue" rgb^*_{3Mm} data: $olv^*_{3,Mm} = olv^*_{3,Mm} [H^*_{a0}]$ (7)

For any input or output device ($m=0$ to 4) it is valid for constant n^*, c^*, l^*, H^*_{a0} :

"red, green, blue" rgb^*_{3m} data: $olv^*_{3m} = 1 - n^* - c^* + c^* olv^*_{3,Mm}$ (8)

Result: device dependent relative CIELAB data of 4 systems $m=1$ to 4:

"red, green, blue" rgb^*_{3m} data: $rgb^*_{3m} = olv^*_{3m}$ (9)