

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=0\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 40.0, 102.8, 136.0, 196.3, 306.2, 328.2$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00y=O</i>	50.4	76.9	64.5	100.4	40.0	1.00	0.00	0.00	
<i>o12y</i>	51.5	73.9	64.9	98.3	41.3	1.00	0.12	0.00	
<i>o25y</i>	54.0	66.7	65.9	93.8	44.6	1.00	0.25	0.00	
<i>o37y</i>	58.2	55.4	67.9	87.7	50.7	1.00	0.37	0.00	
<i>o50y</i>	63.6	41.3	71.0	82.2	59.7	1.00	0.50	0.00	
<i>o62y</i>	70.1	25.7	75.0	79.3	71.0	1.00	0.62	0.00	
<i>o75y</i>	77.2	9.8	79.7	80.4	82.9	1.00	0.75	0.00	
<i>o87y</i>	84.8	-5.7	85.0	85.2	93.8	1.00	0.87	0.00	

KGS40-1A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=0,6\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 38.3, 102.9, 136.2, 196.4, 305.7, 328.1$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00y=O</i>	51.0	75.5	59.6	96.3	38.3	1.00	0.00	0.00	
<i>o12y</i>	52.0	72.6	60.3	94.3	39.7	1.00	0.12	0.00	
<i>o25y</i>	54.5	65.6	61.8	90.1	43.3	1.00	0.25	0.00	
<i>o37y</i>	58.6	54.6	64.4	84.5	49.7	1.00	0.37	0.00	
<i>o50y</i>	63.9	40.8	68.1	79.4	59.0	1.00	0.50	0.00	
<i>o62y</i>	70.3	25.4	72.6	76.9	70.6	1.00	0.62	0.00	
<i>o75y</i>	77.4	9.7	77.7	78.3	82.8	1.00	0.75	0.00	
<i>o87y</i>	84.8	-5.7	83.3	83.5	93.9	1.00	0.87	0.00	

KGS40-2A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=0\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 40.0, 102.8, 136.0, 196.3, 306.2, 328.2$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00o=M</i>	57.2	94.3	-58.4	110.9	328.2	1.00	0.00	1.00	
<i>m12o</i>	55.6	90.3	-43.9	100.4	334.0	1.00	0.00	0.87	
<i>m25o</i>	54.2	86.7	-28.6	91.3	341.6	1.00	0.00	0.75	
<i>m37o</i>	53.0	83.6	-12.6	84.6	351.4	1.00	0.00	0.62	
<i>m50o</i>	52.0	81.1	4.1	81.2	2.9	1.00	0.00	0.50	
<i>m62o</i>	51.3	79.2	21.6	82.1	15.2	1.00	0.00	0.37	
<i>m75o</i>	50.8	77.9	39.2	87.2	26.7	1.00	0.00	0.25	
<i>m87o</i>	50.6	77.2	54.9	94.8	35.4	1.00	0.00	0.12	

KGS41-1A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=0,6\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 38.3, 102.9, 136.2, 196.4, 305.7, 328.1$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00o=M</i>	57.7	93.0	-57.7	109.5	328.1	1.00	0.00	1.00	
<i>m12o</i>	56.1	89.0	-43.7	99.0	334.0	1.00	0.00	0.87	
<i>m25o</i>	54.7	85.4	-28.2	89.9	341.7	1.00	0.00	0.75	
<i>m37o</i>	53.5	82.3	-12.4	83.2	351.4	1.00	0.00	0.62	
<i>m50o</i>	52.6	79.8	4.0	79.9	2.9	1.00	0.00	0.50	
<i>m62o</i>	51.9	77.9	20.9	80.6	15.1	1.00	0.00	0.37	
<i>m75o</i>	51.4	76.6	37.5	85.3	26.0	1.00	0.00	0.25	
<i>m87o</i>	51.1	75.8	51.7	91.8	34.2	1.00	0.00	0.12	

KGS41-2A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=1,2\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 36.9, 103.0, 136.4, 196.4, 305.2, 328.1$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00o=O</i>	51.6	74.2	55.8	92.8	36.9	1.00	0.00	0.00	
<i>o12y</i>	52.6	71.3	56.5	91.0	38.4	1.00	0.12	0.00	
<i>o25y</i>	55.0	64.5	58.4	87.0	42.1	1.00	0.25	0.00	
<i>o37y</i>	59.0	53.8	61.4	81.7	48.7	1.00	0.37	0.00	
<i>o50y</i>	64.3	40.2	65.5	76.9	58.4	1.00	0.50	0.00	
<i>o62y</i>	70.5	25.2	70.3	74.7	70.3	1.00	0.62	0.00	
<i>o75y</i>	77.5	9.6	75.8	76.4	82.7	1.00	0.75	0.00	
<i>o87y</i>	84.9	-5.6	81.6	81.8	93.9	1.00	0.87	0.00	

KGS40-3A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=2,5\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 34.8, 103.2, 136.9, 196.4, 304.3, 328.0$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00y=O</i>	52.7	71.6	49.8	87.3	34.8	1.00	0.00	0.00	
<i>o12y</i>	53.7	68.9	50.7	85.6	36.3	1.00	0.12	0.00	
<i>o25y</i>	56.0	62.4	52.9	81.8	40.2	1.00	0.25	0.00	
<i>o37y</i>	59.8	52.2	56.4	76.9	47.2	1.00	0.37	0.00	
<i>o50y</i>	64.9	39.2	61.0	72.5	57.2	1.00	0.50	0.00	
<i>o62y</i>	71.0	24.6	66.4	70.8	69.6	1.00	0.62	0.00	
<i>o75y</i>	77.8	9.4	72.3	72.9	82.5	1.00	0.75	0.00	
<i>o87y</i>	85.1	-5.5	78.5	78.7	94.0	1.00	0.87	0.00	

KGS40-4A

Interpretation <i>rgb</i> -> <i>olv*</i> - und CIELAB-Daten									
<i>sRGB</i> -Display mit der Leuchtdichte-Reflexion $L_r=1,2\%$									
Bunttonkreis mit 6 Geräte-Bunttönen <i>OYL</i> CVM:									
$h_{ab,a} = 36.9, 103.0, 136.4, 196.4, 305.2, 328.1$									
Elementar-Bunttöne <i>RJGB</i> : $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$									
Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00o=M</i>	58.1	91.8	-57.0	108.0	328.1	1.00	0.00	1.00	
<i>m12o</i>	56.5	87.7	-42.7	97.5	334.0	1.00	0.00	0.87	
<i>m25o</i>	55.1	84.1	-27.7	88.5	341.7	1.00	0.00	0.75	
<i>m37o</i>	54.0	81.0	-12.1	81.9	351.4	1.00	0.00	0.62	
<i>m50o</i>	53.1	78.4	3.9	78.5	2.9	1.00	0.00	0.50	
<i>m62o</i>	52.4	76.5	20.3	79.2	14.8	1.00	0.00	0.37	
<i>m75o</i>	52.0	75.2	36.0	83.4	25.6	1.00	0.00	0.25	
<i>m87o</i>	51.7	74.5	48.9	89.1	33.3	1.00	0.00	0.12	

KGS41-3A

Interpretation *rgb* -> *olv**- und CIELAB-Daten

sRGB-Display mit der Leuchtdichte-Reflexion $L_r=2,5\%$

Bunttonkreis mit 6 Geräte-Bunttönen *OYL*CVM:

$h_{ab,a} = 34.8, 103.2, 136.9, 196.4, 304.3, 328.0$

Elementar-Bunttöne *RJGB*: $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$

Code	<i>L*</i>	<i>a*</i> _a	<i>b*</i> _a	<i>C*</i> _{ab}	$h_{ab,a}$	<i>rgb</i> -> <i>olv*</i>			
<i>m00o=M</i>	59.0	89.3	-55.7	105.2	328.0	1.00	0.00	1.00	
<i>m12o</i>	57.4	85.2	-41.5	94.8	333.9	1.00	0.00	0.87	
<i>m25o</i>	56.1	81.5	-26.9	85.9	341.7	1.00	0.00	0.75	
<i>m37o</i>	55.0	78.4	-11.7	79.3	351.5	1.00	0.00	0.62	
<i>m50o</i>	54.1	75.9	3.8	76.0	2.8	1.00	0.00	0.50	
<i>m62o</i>	53.5	74.0	19.1	76.4	14.5	1.00	0.00	0.37	
<i>m75o</i>	53.0	72.6	33.4	80.0	24.6	1.00	0.00	0.25	
<i>m87o</i>	52.8	71.9	44.4	84.5	31.6	1.00	0.00	0.12	R