

Interpretation *rgb* $\rightarrow$ *olv**- und CIELAB-Daten

sRGB-Display mit der Leuchtdichte-Reflexion $L_r=40\%$

Buntonkreis mit 6 Geräte-Bunttönen OYLCVM:

$h_{ab,a} = 21.9, 107.3, 142.3, 197.9, 293.8, 326.0$

Elementar-Bunttöne **RJGB**: $h_{ab,a} = 25.4, 92.3, 162.2, 271.7$

Code	L^*	a^*_a	b^*_a	C^*_{ab}	$h_{ab,a}$	<i>rgb</i> $\rightarrow$ <i>olv</i> *
<i>o00y=O</i>	76.4	26.2	10.5	28.3	21.9	1.00 0.00 0.00
<i>o12y</i>	76.7	25.5	10.9	27.8	23.2	1.00 0.12 0.00
<i>o25y</i>	77.4	23.8	12.0	26.7	26.8	1.00 0.25 0.00
<i>o37y</i>	78.8	20.8	13.9	25.0	33.7	1.00 0.37 0.00
<i>o50y</i>	80.7	16.5	16.6	23.4	45.1	1.00 0.50 0.00
<i>o62y</i>	83.2	11.0	20.1	22.9	61.2	1.00 0.62 0.00
<i>o75y</i>	86.3	4.5	24.3	24.7	79.4	1.00 0.75 0.00
<i>o87y</i>	89.9	-2.8	29.2	29.3	95.5	1.00 0.87 0.00

R

J