


Entrada i salida: Printer Reflective System FRS06a

Datos del dispositivo (d) o elemental (e) color:

HIC^*_-
código de tono para les colores
esta página:
 $H^*_-= R00Y_-, R25Y_-, ..., B75R_-$

ORS20a; datos adaptados CIELAB (a)					
H^*_-	$L^*=L^*_a$	a^*_a	b^*_a	$C^*_{ab,a}$	$h^*_{ab,a}$
R00Y_100_100_	48.4	66.1	40.2	77.3	31
R25Y_100_100_	56.8	48.0	50.5	69.6	46
R50Y_100_100_	68.6	25.0	63.9	68.6	68
R75Y_100_100_	80.6	4.8	77.2	77.3	86
Y00G_100_100_	90.2	-9.6	88.2	88.7	96
Y25G_100_100_	83.2	-18.4	79.9	81.9	102
Y50G_100_100_	73.3	-31.7	62.7	70.2	116
Y75G_100_100_	62.0	-49.7	43.2	65.8	139
G00B_100_100_	55.8	-65.2	33.8	73.4	152
G25B_100_100_	59.3	-50.3	-9.0	51.0	190
G50B_100_100_	63.0	-30.5	-42.0	51.9	234
G75B_100_100_	45.7	-5.7	-44.6	44.9	262
B00R_100_100_	27.5	25.9	-47.3	53.9	298
B25R_100_100_	38.3	52.6	-28.5	59.8	331
B50R_100_100_	49.5	73.5	-9.0	74.0	353
B75R_100_100_	48.9	69.3	12.9	70.4	10



%Gama
 $u^*_{rel} = 114$
%Regularidad
 $g^*_{H,rel} = 28$
 $g^*_{C,rel} = 38$

FRS06a; datos adaptados CIELAB (a)					
name	$L^*=L^*_a$	a^*_a	b^*_a	$C^*_{ab,a}$	$h^*_{ab,a}$
R_-,Ma	32.5	62.3	46.4	77.7	36
Y_-,Ma	82.7	-3.1	113.9	114.0	91
G_-,Ma	39.4	-61.8	45.8	76.9	143
C_-,Ma	47.8	-26.8	-34.2	43.4	231
B_-,Ma	10.1	55.1	-61.0	82.2	312
M_-,Ma	34.5	80.6	-33.9	87.5	337
N_-,Ma	6.2	0.0	0.0	0.0	0
W_-,Ma	91.9	0.0	0.0	0.0	0
R_-,CIE	39.9	58.7	27.9	65.0	25
Y_-,CIE	81.2	-2.8	71.5	71.6	92
G_-,CIE	52.2	-42.4	13.6	44.5	162
B_-,CIE	30.5	1.4	-46.4	46.4	271

