




**Achromatic receptor-response function**  
 $Q_{ab}(x_r/a) = a - b \ln\left[\frac{1}{1 + \sqrt{2}e^{(x_r/a)}}\right] - b$   
 $L_u =$  surround luminance  
 with  $x_r = \log[L/L_u]$  ( $L =$  test luminance)  
 $L_u =$  surround luminance  
 $Q_{ab}(x_r/a) = \frac{b}{\ln 2} \ln\left[\frac{1}{1 + \sqrt{2}e^{(x_r/a)}}\right] - b$   
**function values for  $b=1$  and any  $a>0$ :**  
 $Q_{a1}(x_r/a \rightarrow -\infty) = -1 \quad x = \log L, u = \log L_u$   
 $Q_{a1}(x_r/a = 0) = 0 \quad x_r = \log[L/L_u]$   
 $Q_{a1}(x_r/a \rightarrow +\infty) = +1 \quad -x = u$




**Achromatic colour vision with relative luminance**  
**Mathematical equations with hyperbel functions**  
 $F(x) = \tanh(x) = \frac{e^x - e^{-x}}{e^x + e^{-x}} = \frac{u(x)}{v(x)} \quad u'(x) = v(x) \quad (1)$   
 $\frac{dF(x)}{dx} = \frac{u'(x)v(x) - u(x)v'(x)}{v^2(x)} = \frac{v^2(x) - u^2(x)}{v^2(x)} \quad (2)$   
 $\frac{dF(x)}{dx} = \frac{[e^x + e^{-x}][e^x + e^{-x}] - [e^x - e^{-x}][e^x - e^{-x}]}{[e^x + e^{-x}]^2} \quad (3)$   
 $\frac{dF(x)}{dx} = \frac{4}{[e^x + e^{-x}]^2} = \frac{1}{\cosh^2(x)} \quad (4)$




**Achromatic receptor-response function**  
 $Q_{ab}(x_r/a) = a - b \ln\left[\frac{1}{1 + \sqrt{2}e^{(x_r/a)}}\right] - b$   
 $L_u =$  surround luminance  
 with  $x_r = \log[L/L_u]$  ( $L =$  test luminance)  
 $L_u =$  surround luminance  
 $Q_{ab}(x_r/a) = \frac{b}{\ln 2} \ln\left[\frac{1}{1 + \sqrt{2}e^{(x_r/a)}}\right] - b$   
**function values for  $b=1$  and any  $a>0$ :**  
 $Q_{a1}(x_r/a \rightarrow -\infty) = -1 \quad x = \log L, u = \log L_u$   
 $Q_{a1}(x_r/a = 0) = 0 \quad x_r = \log[L/L_u]$   
 $Q_{a1}(x_r/a \rightarrow +\infty) = +1 \quad -x = u$




**Achromatic colour vision with relative luminance**  
**Mathematical equations with hyperbel functions**  
 $F(x, a) = \tanh(x/a) = \frac{e^{x/a} - e^{-x/a}}{e^{x/a} + e^{-x/a}} = \frac{u(x/a)}{v(x/a)} \quad (1)$   
 $\frac{dF(x, a)}{dx} = \frac{u'(x/a)v(x/a) - u(x/a)v'(x/a)}{v^2(x/a)} \quad (2)$   
 $\frac{dF(x, a)}{dx} = \frac{v^2(x/a) - u^2(x/a)}{a v^2(x/a)} \quad (3)$   
 $\frac{dF(x, a)}{dx} = \frac{4}{a [e^{x/a} + e^{-x/a}]^2} = \frac{1}{a \cosh^2(x/a)} \quad (4)$




**Mathematical equations of hyperbel functions**  
 See: Papula, L. (2003), *Mathematische Formelsammlung, Vieweg*  
 $\sinh(x) = \frac{e^x - e^{-x}}{2} \quad (1), \quad \cosh(x) = \frac{e^x + e^{-x}}{2} \quad (2)$   
 $\tanh(x) = \frac{\sinh(x)}{\cosh(x)} = \frac{e^x - e^{-x}}{e^x + e^{-x}} \quad (3)$   
 $\tanh(x/2) = \frac{\sinh(x)}{\cosh(x)+1} = \frac{e^{x/2} - e^{-x/2}}{e^{x/2} + e^{-x/2}} \quad (4)$   
 $\sinh^2(x) + \cosh^2(x) = 1 \quad (5)$



**Achromatic colour vision with relative luminance**  
**Mathematical equations with potential functions**  
 $F(L) = \frac{L^m - L^{-m}}{L^m + L^{-m}} = \frac{u(L)}{v(L)} \quad u'(L) = m(L^{m-1} - L^{-m-1}) \quad (1)$   
 $\frac{dF(L)}{dL} = \frac{u'(L)v(L) - u(L)v'(L)}{v^2(L)} \quad (2)$   
 $u'(L)v(L) - v'(L)u(L) = m \{ [L^{2m-1} + L^{-m-1}][L^m + L^{-m}] - [L^{2m-1} - L^{-m-1}][L^m - L^{-m}] \} \quad (3)$   
 $= m(L^{2m-1}L^1 + L^{-1}L^{-2m} - L^{2m-1}L^{-1} - L^{-2m+1}L^1) = 4mL^{-1}$   
 $\frac{dF(L)}{dL} = \frac{4m}{(L(L^m + L^{-m}))^2} \quad (4)$



**Mathematical equations of hyperbel functions**  
 See: Papula, L. (2003), *Mathematische Formelsammlung, Vieweg*  
 $\sinh(x) = \frac{10^{x/a} - 10^{-x/a}}{2} \quad (1), \quad \cosh(x) = \frac{10^{x/a} + 10^{-x/a}}{2} \quad (2)$   
 $\tanh(x) = \frac{\sinh(x)}{\cosh(x)} = \frac{10^{x/a} - 10^{-x/a}}{10^{x/a} + 10^{-x/a}} \quad (3)$   
 $\tanh(x/2) = \frac{\sinh(x)}{\cosh(x)+1} = \frac{10^{x/2a} - 10^{-x/2a}}{10^{x/2a} + 10^{-x/2a}} \quad (4)$   
 $\sinh^2(x) + \cosh^2(x) = 1 \quad (5)$



**Achromatic colour vision with relative luminance**  
**Equations with hyperbel and potential functions**  
 $F_{ab}(x_r, a) = b \tanh(x_r/a) = b \frac{e^{x_r/a} - e^{-x_r/a}}{e^{x_r/a} + e^{-x_r/a}} \quad x_r < 0 \quad (1a)$   
 $\frac{dF_{ab}(x_r, a)}{dx_r} = \frac{4b}{a [e^{x_r/a} + e^{-x_r/a}]^2} = \frac{b}{m-1} \ln(10) a \quad (5a)$   
 $F_{ab}(L_r, m) = b \tanh(x_r/a) = b \frac{L^m - L^{-m}}{L^m + L^{-m}} \quad L_r < 1 \quad (1b)$   
 $\frac{dF_{ab}(L_r, m)}{dL_r} = \frac{4bm}{L_r [L_r^m + L_r^{-m}]^2} = \frac{b}{m-1} \ln(10) a \quad (5b)$

TUB-test chart eer2; Model of normalized response functions  $F_{ab}(x_r)$ ,  $Q_{ab}(x_r)$  &  $P_{ab}(L_r)$ , and derivation, Tangens hyperbolicus  $\tanh(x_r)$  and modified functions with  $e^{x_r}$ ,  $10^{x_r}$ , and  $L_r$