



Line element of *Stiles* (1946)  
 with „cone values”  $L, M, S$   
 separate colour response functions  
 $F(L) = i \ln(1+9L)$   
 $F(M) = i \ln(1+9M)$   
 $F(S) = i \ln(1+9S)$   
 Taylor-derivations:  
 $\Delta F(L, M, S) = \frac{dF}{dL} \Delta L + \frac{dF}{dM} \Delta M + \frac{dF}{dS} \Delta S$   
 $= \frac{9i}{1+9L} \Delta L + \frac{9i}{1+9M} \Delta M + \frac{9i}{1+9S} \Delta S$

feb20-1N

Line element of *Vos&Walraven* (1972)  
 with „cone values”  $L, M, S$   
 separate colour response functions  
 $F(L) = -2i \sqrt{L}$   
 $F(M) = -2i \sqrt{M}$   
 $F(S) = -2i \sqrt{S}$   
 Taylor-derivations:  
 $\Delta F(L, M, S) = \frac{dF}{dL} \Delta L + \frac{dF}{dM} \Delta M + \frac{dF}{dS} \Delta S$   
 $= -i \frac{\Delta L}{\sqrt{L}} - i \frac{\Delta M}{\sqrt{M}} - i \frac{\Delta S}{\sqrt{S}}$

feb20-2N





functions  $q[k(x-u)]$   
 „achromatic signal”-description  
 with  $x = \log L$  ( $L = \text{luminance}$ )  
 $u = \log L_u$  ( $L_u = \text{surround luminan.}$ )  
 $q[k(x-u)] = 1 + 1/[1 + \sqrt{2}e^{k(x-u)}]$   
 function values:  
 $q[k(x-u) \rightarrow +\infty] = 1$   
 $q[k(x-u) = 0] = \sqrt{2}$   
 $q[k(x-u) \rightarrow -\infty] = 2$

feb20-3N

„achromatic signal”-description  
 functions  $Q_{1m}[k(x-u)]$   
 with  $x = \log L$  ( $L = \text{luminance}$ )  
 $u = \log L_u$  ( $L_u = \text{surround luminan.}$ )  
 $Q_{1m}[k(x-u)] = \frac{1}{\ln \sqrt{2}} \ln q[k(x-u)] - m$   
 function values with  $l = m = 1$ :  
 $Q[k(x-u) \rightarrow +\infty] = 1$   
 $Q[k(x-u) = 0] = 0$   
 $Q[k(x-u) \rightarrow -\infty] = -1$

feb20-4N





„achromatic signal” discrimination  
 as function of relative light density  
 $h = \ln H = k(x-u)$   $\ln = \text{natural log.}$   
 $Q' = \frac{d}{dH} [\ln\{1 + 1/(1 + \sqrt{2}H)\}] / \ln \sqrt{2}$   
 $= -\sqrt{2} / [\ln \sqrt{2} (1 + \sqrt{2}H)(2 + \sqrt{2}H)]$   
 function values:  
 $Q'[k(x-u) \rightarrow +\infty] = 0$   
 $Q'[k(x-u) = 0] = -0,5$   
 $Q'[k(x-u) \rightarrow -\infty] = 0$

feb20-5N

luminance discrimination  
 possibility  $L/\Delta L$  as function of  $H$   
 with:  $L = 10^k H = e^{k \ln 10 \log k(x-u)}$   
 $dL/dx = \ln 10 L$   $dH/dx = k H$   
 $u \text{ follows: } L/\Delta L = [kH] / (dH \ln 10)$   
 $\frac{L}{dL} = \text{const } H / [(1 + \sqrt{2}H)(2 + \sqrt{2}H)]$   
 function values:  
 $Q'[k(x-u) \rightarrow +\infty] = 0$   
 $Q'[k(x-u) = 0] = \text{maximum}$   
 $Q'[k(x-u) \rightarrow -\infty] = 0$

feb20-6N





double line element of *Richter*  
 (1987) for the lighting technic with  
 luminance  $L = \bar{F}(L, \bar{u}, \bar{v})$   
 luminance signal function  $F(L)$   
 $F(L) = iQ(H) = \begin{cases} i Q(\bar{H}) & (x < u) \\ \bar{i} Q(\bar{H}) & (x \geq u) \end{cases}$   
 with:  $k=1,4$   $\bar{k}=1$   $i=1$   $\bar{i}=-2$   
 $x = \log L$   $u = \log L_u$   
 $H = e^{k(x-u)}$ ,  $\bar{H} = e^{\bar{k}(x-u)}$ ,  $\bar{u} = e^{\bar{k}(x-u)}$

feb20-7N

double line element of *Richter*  
 (1987) for the lighting technic with  
 luminance  $L = \bar{F}(L, \bar{u}, \bar{v})$   
 luminance signal function  $F(L)$   
 $F(L) = iQ(H)$   $H = e^{k(x-u)}$   
 $Q[\ln\{1 + 1/(1 + \sqrt{2}H)\}] / \ln \sqrt{2} - 1$   
 Taylor-derivations:  
 $\Delta F(L) = \frac{dF}{dL} \Delta L = i \frac{dQ}{dH} \Delta H$   
 $= -i \sqrt{2} \Delta H / [\ln \sqrt{2} (1 + \sqrt{2}H)(2 + \sqrt{2}H)]$

feb20-8N



see similar files of the whole serie: <http://farbe.li.tu-berlin.de/feb2/feb201n1.txt>  
 technical information: <http://farbe.li.tu-berlin.de> or <http://color.li.tu-berlin.de>

TUB registration: 20231201-feb2/feb201n1.txt /ps  
 application for evaluation and measurement of display or print output  
 TUB material: code=th4ta